No. E824MCGL

SHARP SERVICE MANUAL

SHAR-03693



MODEL EL-5808

CONTENTS

1. SPECIFICATIONS

(1) Keys' layout

F	DRG	♪	POWER OFF	POWER ON/C
$1/x$	$\sin^{-1}$	$\cos^{-1}$	$\tan^{-1}$	n !
hyp	sin	cos	tan	C E
→D.MS	10^x	log	$\rightarrow x\,y$	STAT
→DEG	e^x	ln	$r\theta$	↕
π	3 ⌐	⌐	Δ %	$n\Sigma x$
EXP	y^x	x^2	(	)
7	8	9	÷	$\bar{x}\ \Sigma x^2$ / $x \rightarrow$ M
4	5	6	×	S σ / RM
1	2	3	−	DATA CD / M +
0	+/−	•	+	=

3693

(2) Display: FEM type liquid crystal
8 digits for mantissa part
2 digits for exponent part

- Character's shape



M: Memory symbol
−: Minus symbol
E: Error symbol
STAT: Statistical program symbol
DEG: Degree symbol
RAD: Radian symbol
GRAD: Grad symbol
X10: Exponent portion displays symbol
●: Battery indicator

(3) Automatic power off function: 7±3 minutes
(4) LSI: SC3759
(5) Dimensions: 5(H) x 71(W) x 127(D) mm
3/16"(H) x 2-25/32"(W) x 5"(D)
(6) Power supply: Silver oxide battery G-10G x 2
(Please note that only Eveready model 389, and Ray-O-Vac model RW49 or equivalent should be used)
(7) Operating time: Approx. 600 hours of operation at silent mode.
(Display 5555. at ambient temperature 20°C (68°F))
Approx. 450 hours of operation
(1111 [x] 5 [=] at ambient temperature 20°C (68°F))

2. SERVICING

(1) Disassembly Procedure
1. Turn over the set.
2. Take out the bottom panel after loosing the two screws that is securing the bottom panel (Fig. 1).
3. Pull out the two batteries (Fig. 2).
4. Carefully peel off the black masking sheet which is applied to the chassis. (Fig. 2)
5. Remove soldered leads of the PWB at three portions (Fig. 3 * mark)
6. Take out the chassis after remove the two pawls that is securing the chassis (Fig. 3  mark)
7. Take out the PWB unit after remove the three pawls that is securing the PWB unit. (Fig. 3  mark)



Fig. 1



Fig. 2



Fig. 3

(2) Control adjustment

Keep Vin to 3.15±0.05V make sure that the signal T_1 is within the range of 1.55msec≦T_1≦1.65 msec. If the above value is not satisfied, adjust it by using the control variable resistor.



(3) All reset switch

This is located on the back of the calculator. You should use this switch only when you can't clear the machine by touching ON/C key after the battery replacement.

3. CIRCUIT DIAGRAM



4. PARTS & SIGNAL POSITION



5. PARTS LIST

NO.	PARTS CODE	DESCRIPTION	NEW PARTS MARK	EXPORT PRICE RANK
1	CCABBI976CC01	Top cabinet	N	A R
2	PFiLWI188CCZZ	Filter	N	A E
3	PSLDPI129CCZZ	Display mask	N	A D
4	DANGT0412CSZZ	Key panel	N	A K
5	PGUMMI133CCZZ	Key rubber	N	A H
6	PGUMMI134CCZZ	Key rubber (4key)	N	A C
7	PGUMMI136CCZZ	Key rubber (Fkey)	N	A C
8	PSPAPI157CCZZ	Switch spacer (5key)	N	A B
9	PZETLI219CCZZ	Key spacer	N	A A
10	PCUSSI079CCZZ	L. C. D cushion A		A A
11	PSHE-1045CCZZ	L. C. D cushion B		A A
12	PCUSGI099CCZZ	L. C. D cushion C	N	A A
13	DUNTK5053CSZZ	P. W. B unit (with L.S.i, L.C.D and electronics parts)	N	B K
14	DWAKM0416CSZZ	Chassis (with buzzer)	N	A K
15	PSLDPI128CCZZ	Sheet	N	A B
16	RALMBI003CCZZ	Buzzer		A G
17	PHŌKWI002CCZZ	Hook		A A
18	PSHEPI028CCZZ	Sheet fixing book		A A
19	PZETLI221CCZZ	Mylar sheet (for top cabinet)	N	A A
20	QTANZI205CCZZ	Battery terminal (+)	N	A C
21	QTANZI206CCZZ	Battery terminal (−)	N	A C
22	QTANZI207CCZZ	Battery terminal (+, −)	N	A B
23	PZETLI220CCZZ	Mylar sheet (for bottom panel)	N	A A
24	HDECAI423CCZZ	Bottom panel (w/o mylar sheet)	N	A L
25	UBAGZI131CCZZ	Book type case	N	A H
26	XBSSC20P04000	Screw		A A
27	LANGTI213CCZZ	Buzzer angle		A B
28	QCNTMI036CCZZ	All reset switch contact	N	A B
	PPAPMI003CCZZ	Memo pad		A A
	SPAKC2802CCZZ	Packing case (U. S. A)	N	A B
	SPAKC2804CCZZ	Packing case (Other countries)	N	A B
	TCAUKI123CCZZ	Caution lavel		A A
	TiNSE2239CCZZ	Instruction book (English)	N	A D
	TiNSM2240CCZZ	Instruction book (E, F, G, S)	N	A G
	RC-CZI008CCZZ	Capacitor 82PF 50WV	N	A A
	RC-KZI007CCZZ	Capacitor 100PF		A B
	RC-SZI007CCZZ	Capacitor 1μF		A F
	RVR-M3511QCZZ	Variable resistor 300Kohm		A D
	VHiSC3579//-1	L. S. i SC3579	N	B E
	VRC-MT2BGI01K	Resistor 1/8W 100ohm ±10%		A A

6. PARTS GUIDE



7. SIGNAL WAVEFORM



SHARP CORPORATION
Industrial Instrument Group
Service Control Dept.
Yamatokoriyama, Nara 639-11, Japan
July 1978